

## Security drawers with time delay RSH 2000 DK

Robur introduced the Time Delay Drawer Pedestal in Northern Europe more than fourty years ago. Since then, almost one hundred thousands units have been installed. Many different models have been developed at customers' request through the years.





Modern design painted in silver metallic.



The unit is equipped with Robur's unique pincode lock, which is integrated into the construction. From the keyboard individual codes and time delays can easily be programmed for each drawer.

The unit has a keylock switch which activates the pincode-lock.



The top drawer has one box for notes with 9 dividers. The second drawer have four movable dividers. The third drawer has a chute. The bottom drawer has one insert box to receive and protect the banknotes deposited through the chute.



Each unit is connected to the mains 240 A.C. by a transformer. Operating Voltage 12 A.C. Maximum power use is 1,6A. A backup battery is available on request.



The unit is prepared for anchoring with two holes at the bottom. (Bolts are not included).

## **PRODUCT SPECIFICATIONS**

	RSH 2000 DK
External measurements  H * W * D* mm	800 * 428 * 500
Internal measurements of the two upper drawers	112 * 330 * 389
Internal measurements of the bottom drawer	131 * 330 * 389
Internal measurements of the deposit slot	69 * 330
Weight kg	100
Deposit function	Yes

## **STANDARD FITTINGS**



Box for notes With 9 dividers



Two stickers are supplied with the security drawer, one should be placed on the unit and the other one should be placed at the entrance.





Movable divider

## **OPTIONAL FITTINGS**

Coin tray - €

1-Cent, 2-Cent, 5-Cent, 10-Cent, 20-Cent, 50-Cent, 1-€ och 2-€

- Battery backup box
- Silent alarm
- Emergency lock

We reserve the right to alter the specification without prior notice.



**Head office:** Robur Safe AB Lundbyvägen 8 311 68, Slöinge Sweden



**L** + 46 346 260 260



☑ info@robursafe.com



www.robursafe.com