



Security drawers with time delay

RSH 2000 NF – Robur Office Line

Robur introduced the Time Delay Drawer Pedestal in Northern Europe more than forty years ago. Since then, almost one hundred thousands units have been installed. Many different models have been developed at customers' request through the years. The RSH NF serie is designed for safety storage of valuable confidential business documents.



RSH 2000 NF-2



RSH 2000 NF-2H



RSH 2000 NF-4



Modern design painted in silver metallic.



The unit is equipped with Robur's unique pincode lock, which is integrated into the construction. From the keyboard individual codes and time delays can easily be programmed for each drawer.

The unit has keylock switch which activates the pincode-lock.



One stationary tray in the top drawer of RSH 2000 NF-2 and NF-2H.

Two movable dividers in the upper drawer of RSH 2000 NF-2 and NF-2H.

No internal fittings in RSH 2000 NF-4.



Each unit is connected to the mains 230-240V A.C. by a transformer.

Operating Voltage 12 A.C. Maximum power use is 1,6A.

A backup battery is available on request.



The height can be adjusted.

NF-4 is prepared for anchoring with two holes at the bottom. (Bolts are not included).

PRODUCT SPECIFICATIONS

	RSH 2000 NF-2	RSH 2000 NF-2H	RSH 2000 NF-4
Model			
External measurements H * W * D* mm	610 * 428 * 605	720 up to 745 * 428 * 605	1288 up to 1313 * 428 * 605
Internal measurements of the drawers H * W * D* mm	Upper: 108 * 330 * 530 Bottom: 278 * 330 * 530	Each: 278 * 330 * 530	Each: 278 * 330 * 530
Weight kg	67	76	131
Height adjustment	If the wheels are removed the height will be 536mm.	The height can be adjusted with adjustable feet between 720 and 745 mm. Height without the adjustable feet: 708mm.	The height can be adjusted with adjustable feet between 1285 and 1310 mm. Height without the adjustable feet: 1273mm.
Anchoring	Has wheels for easier moving.	Placed under the workplace and attached to the desk.	Prepared for anchoring to the floor.
Drawers	One pencil drawer and two safety drawers.	One pencil drawer and two safety drawers.	Four safety drawers.
Standard fittings	 Plastic tray For pens, binders etc.  Movable dividers	 Plastic tray For pens, binders etc.  Movable dividers	No fittings.



Two stickers are supplied with the security drawer, one should be placed on the unit and the other one should be placed at the entrance.

OPTIONAL FITTINGS

- Silent alarm
- Battery backup box
- Emergency lock

We reserve the right to alter the specification without prior notice.



Head office:
Robur Safe AB
Lundbyvägen 8
311 68, Slöinge
Sweden

 + 46 346 260 260
 info@robursafe.com
 www.robursafe.com